

LEXRON Provides Safe and Efficient LFP Battery Solutions.

LXR series adopt best value Lityum cells, with the BMS system independently designed by LEXRON. series and parallel use, is energy storage, marine and other fields. IP65 protection, support an ideal choice for outdoor, small

Features

- Bluetooth access to show functions like
- Lithium iron Phosphate Battery(Lityum)
- Eco-friendly
- Special protection plate
- Multiple safety protection
- · Intelligent balancing function
- 20 Years Designed service life

Mechanical Specifications

ABS Case Material

Cell Type-Chemistry **Prismatic Lityum**

Terminal Type **M8**

IP Grade **IP65**

BMS Characteristics

Recommended Charge Current 100A

Maximum Charge Current 100A

Maximum Continuous Discharge Current 100A

Recommended Charge Voltage 27.8~28.6V

Max Charge Voltage 29.2V

Overcharge Protection Voltage 29.4~29.8V

Charge Mode cc/cv

Discharge Cut-off Voltage 21.6V

Basic Performance

Nominal Voltage 25.6V

Nominal Capacity 100Ah

Standard Discharge Time 100A@60min

2.56KWh Capacity

<= 15mΩ

Self Discharge <=2%/Month

Square 100Ah Cells

Cycle Life 4000 times(80%DOD)

522*238*223 Size (mm)

19.5 Weight (kg)



Charge Performance

10_{0A} Rated Charge Current 1004 Maximum Charge Current

27.8~28.6V Rated Charge Voltage

> 29.2V(0.5~1.5S) Charge Cut-off Voltage

<28.8V Reconnect Voltage

< 28V Balancing Voltage

<= 2 System Series

Discharge Performance

Rated Discharge Current 100A

Pulse Current(<=5S) 2004

Rated Discharge Cut-off Voltage 21.6V

Minimum Discharge Cut-off Voltage >20.5V

Short Circuit Protection

>20.8V

200~600 µs

Short Circuit Current Approx. 1000A

Temperature Performance

-20~65°C Discharge Temperature

-5~60°C Charge Temperature

-10~40°C Storage Temperature

65°C High Temperature Cut-off

45°C Reconnect Temperature


Compliance

Reconnect Voltage

Certifications CE/UN38.3/UL1973/IEC62619

Transport Appraisal UN3480,CLASS 9

Size













Characteristics Curve









Cautions

- Do NOT short circuit, crush or disassemble.
- 2. Do NOT heat or incinerate.
- Do NOT immerse in any liquid.
- Store at 50% capacity. Recharge every 3 months. The storage area should be clean, cool, dry and ventilated.
- Disconnect charging source prior to connecting or disconnecting battery terminals.
- Do not dispose of batteries in a fire as they can explode.
- Do not open, alter, or mutilate batteries.
- Do not mix different types and brands of lithium—ion batteries.
- Do not dispose in trash, follow local regulations and manufacturer's instruction.
- See installation instructions before connecting to the supply.
- 11. The battery cabinet receives power from more than one source. Disconnection of all DC sources is required to De-energize this unit before installing or servicing. Wait 5 minutes before opening the unit.
- Do not install on or over combustible surfaces.





ACS ENERJI

ITOB OSB Mah. Ekrem Demirtas Cad. No: 44 Menderes - IZMIR